

**SPECIFICATION SHEET**

**JFW MODEL 50PA-556**

**PROGRAMMABLE ATTENUATOR ASSEMBLY**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

Frequency Range	700-3000 MHz
Configuration	Four individually controlled solid-state programmable attenuators
Impedance	50 Ohms nominal
Attenuation Range	0-127 dB in 1 dB steps
VSWR	1.6:1 maximum
Attenuation Accuracy (guaranteed monotonic)	± 0.5 dB or 2% (whichever is greater)
Insertion Loss	6.0 dB maximum
RF Input Power	+20 dBm average
Switching Speed	5 microseconds typical (after command is received and processed) (3 milliseconds typical processing time)
AC Supply	100-240 VAC @ 47-63 Hz
Manual Control	20-Button Keypad and LCD display
Remote Control	RS-232 (9600, 19200, or 38400 Baud) Ethernet (TCP, 10/100, up to 4 users)
Remote Commands	Attenuator Control Commands: Set Attenuator, Set Attenuator with Response, Read Attenuator, Set All Attenuators, Read All Attenuators, Set Multiple Attenuator, Fade Attenuator, Variable Handover, Store, Recall  System Commands: Identification, Pause -RS-232 Only: Change Baud -Ethernet Only: Disconnect, Close, Message, Clear
RF Connector	SMA or N female
Operating Temperature Range	0°C to +50°C

**--CONTINUED--**

**SPECIFICATION SHEET**  
**JFW MODEL 50PA-556**  
**PROGRAMMABLE ATTENUATOR ASSEMBLY**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

Physical Size

See outline drawing 092-6249 (SMA)  
092-6293 (N)



ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	12/09/2009		CLK 12/09/2009				