



偉詮電子股份有限公司
Weltrend Semiconductor, Inc.

WT9101

Video Amplifier System with OSD & DACs

Data Sheet

Preliminary

REV. 0.92

Feb, 5, 2002

**The information in this document is subject to change without notice.
© Weltrend Semiconductor, Inc. All Rights Reserved.**

新 竹 市 科 學 工 業 園 區 工 業 東 九 路 24 號 2 樓
2F, No. 24, Industry E. 9th RD., Science-Based Industrial Park, Hsin-Chu, Taiwan
TEL:886-3-5780241 FAX:886-3-5794278.5770419

PIN DESCRIPTION

Pin No.	Pin Name	Description
1 2 3	Red OSD Input Green OSD Input Blue OSD Input	These inputs accept standard TTL or CMOS inputs. Each color is either fully on (logic high) or fully off (logic low). Unused pins should be connected to ground with a 47k resistor.
4	OSD Select	This input accepts a standard TTL or CMOS input. H = OSD L = Video Connect to ground with a 47k resistor if not using OSD.
5 6 7	Red Video In Green Video In Blue Video In	Video inputs. These inputs must be AC coupled with a 0.047 μ F cap. DC restoration is done at these inputs. A series resistor of about 33 Ω and external ESD protection diodes should also be used for ESD protection.
8	Analog Ground	Ground Pin for the analog circuits of the WT9101
9	Vcc	Power supply pin for WT9101
10	V _{REF} ^R _{EXT}	Sets the internal current sources through a 10 k Ω 1% external resistor. Resistor value and accuracy is critical for optimum operation of the WT9101
11	SDA	The I ² C data line. A pull-up resistor of about 2 k Ω should be connected between this pin and +5V. A 300 Ω resistor should be connected in series with the data line for protection against arcing.
12	SCL	The I ² C Clock line. A pull-up resistor of about 2k Ω should be connected between this pin and +5V. A 300 Ω resistor should be connected in series with the clock line for protection against arcing.
13 14 15 16	DAC4 DAC3 DAC2 DAC1	DAC outputs for cathode cut-off adjustments and brightness control. DAC 4 can be set to change the outputs of the other three DACs, acting as the brightness control. The DACS are set through the I ² C bus.
17	Digital Ground	Ground Pin for the digital circuits of the WT9101
18 19 20	Blue Video Out Green Video Out Red Video Out	Video outputs of the WT9101. The ideal driver for this part is CRT driver, which has the necessary gain of 26 dB or 20 V/V.
21	V _{REF} ^R _{Out}	A 0.1 μ F capacitor must be placed close to this pin for decoupling the internal Vref. This pin may be used for an external voltage reference with proper buffering
22	ABL	The Auto Beam Limit control reduces the gain of the video amplifier in response to a control voltage proportional to the CRT beam current. The ABL acts identically on all three channels. ABL is required for CRT life and X-ray protection



WT9101

Data Sheet Rev. 0.92

Pin No.	Pin Name	Description
23	Clamp Pulse	This input accepts a standard TTL or CMOS input. A positive signal activates the clamp pulse for DC restoration of the video input. The AC coupling capacitors at the video inputs are used for holding the DC correction voltage, eliminating the need for additional capacitors
24	H Flyback	H flyback is an analog signal input from the monitor horizontal scan. The WT9101 is able to generate an accurate blanking pulse in the video outputs from this input. The horizontal flyback from the monitor must be a clean signal, with no ringing or other noise on the signal