## RTAN430X SERIES


TRANSISTOR WITH RESISTOR FOR MUTING APPLICATION SILICON NPN EPITAXIAL TYPE


#### **FEATURE**

- •Built-in bias resistor (R1=4.7k $\Omega$ )
- •Small package for easy mounting.
- ·High reverse hFE
- Small collector to emitter saturation voltage.
   VCE(sat)=10mV(TYP.)(@IC=10mA/IB=0.5mA)
- -Low on Resistance Ron=0.80 Ω (TYP.) (@VI=5V)

#### **APPLICATION**

muting circuit, switching circuit





# RTAN430X SERIES

TRANSISTOR WITH RESISTOR FOR MUTING APPLICATION SILICON NPN EPITAXIAL TYPE

## MAXIMUM RATING(Ta=25°C)

SYMBOL	PARAMETER	RATING				
		RTAN430T2	RTAN430U	RTAN430M	RTAN430C	UNIT
V <sub>CBO</sub>	Collector to Base voltage	40				
$V_{EBO}$	Emitter to Base voltage	40				
$V_{CEO}$	Collector to Emitter voltage	20				
Ιc	Collector current	400				
P <sub>c</sub>	Collector dissipation(Ta=25°C)	125(※)	150	200		mW
Tj	Junction temperature	+125	+150			°C
Tstg	Storage temperature	−55 <b>~</b> +125	−55 <b>~</b> +150			°C


### ELECTRICAL CHARACTERISTICS (Ta=25°C)

\*\*package mounted on 9mm × 19mm × 1mm glass-epoxy substrate.


SYMBOL	PARAMETER	TEST CONDITION	LIMIT			LINIT
		TEST CONDITION	MIN	TYP	MAX	UNIT
V <sub>(BR)CBO</sub>	C to B break down voltage	$I_{c}=50 \mu A, I_{E}=0mA$	40			V
$V_{(BR)EBO}$	E to B break down voltage	$I_{E}=50 \mu A, I_{C}=0mA$	40			V
$V_{(BR)CEO}$	C to E break down voltage	I <sub>c</sub> =1mA, R <sub>BE</sub> =∞	20			٧
I <sub>CBO</sub>	Collector cut off current	$V_{CB}$ =40V, I <sub>E</sub> =0mA			0.5	μΑ
I <sub>EBO</sub>	Emitter cut off current	$V_{EB}$ =40V, I <sub>C</sub> =0mA			0.5	μΑ
h <sub>FE</sub>	DC forward current gain	$V_{CE}$ =5V, I $_{C}$ =10mA	820		2500	_
$V_{CE(sat)}$	C to E saturation voltage	$I_{C}$ =10mA, $I_{B}$ =0.5mA		10		mV
$R_1$	Input resistance		3.29	4.7	6.11	kΩ
f <sub>⊤</sub>	Gain band width product	$V_{CE}$ =10V, I <sub>E</sub> =-10mA, f=100MHz		38		MHz
R <sub>on</sub>	Output "ON" resistance	$V_i$ =5V, $R_L$ =1k $\Omega$		0.80		Ω


## TYPICAL CHARACTERISTICS








## collector current - Input on voltage













Marketing division, Marketing planning department 6-41 Tsukuba, Isahaya, Nagasaki, 854-0065 Japan

#### Keep safety first in your circuit designs!

ISAHAYA Electronics Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (1) placement of substitutive, auxiliary, (2) use of non-farmable material or (3) prevention against any malfunction or mishan.

#### Notes regarding these materials

- These materials are intended as a reference to our customers in the selection of the ISAHAYA products best suited to the customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging
- Customer's application; they don't convey any license under any intellectual property rights, or any other rights, belonging ISAHAYA or third party.

  ISAHAYA or third party.

  ISAHAYA Electronics Corporation assumes no responsibility for any damage, or infringement of any third party's rights, originating in the use of any product data, diagrams, charts or circuit application examples contained in these materials.

  All information contained in these materials, including product data, diagrams and charts, represent information on products at the time of publication of these materials, and are subject to change by ISAHAYA Electronics Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact ISAHAYA Electronics Corporation or an authorized ISAHAYA products distributor for the latest product information before purchasing product listed becomes
- ISAHAYA Electronics Corporation products are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact ISAHAYA electronics corporation or an authorized ISAHAYA products distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.

  The prior written approval of ISAHAYA Electronics Corporation is necessary to reprint or reproduce in whole or in part these
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.

  •Please contact ISAHAYA Electronics Corporation or authorized ISAHAYA products distributor for further details on these
- materials or the products contained therein.