



# APPLIED CONCEPTS INC.

397 Route 281 - P.O. BOX 453  
Tully, New York 13159-0453  
Phone: (315) 696-6676 Fax: (315) 696-9923  
[www.acipower.com](http://www.acipower.com)

# AC-1421

## CCFL INVERTER

(For Single Tube Applications)

## PRODUCT DATA SHEET

05/29/03

The AC-1421 is designed to drive 1 CCFL to a nominal current level of 6.0mA.

Intensity control (0-100%) is accomplished by the user providing a variable dc level of 0V(off) to 5V(full-on) at pin 3 of CON1.

A +5V level is available at pin 4 of CON1 for powering the high-side of the intensity control potentiometer.

The lamp output is open and short circuit protected.

### Specifications:

- Vin = +12V +/- 10%
- CCFL strike voltage = 1400Vrms @ Vin=12V
- CCFL tube current = 6.0mA/tube @ 100% intensity/Vin=12V
- Recommended CCFL sustaining voltage = 400Vrms - 600Vrms
- Nominal tube current frequency = 41kHz +/- 10%
- Nominal pwm frequency = 98Hz +/- 3%
- Pwm duty cycle range = 0 to 100%
- Average electrical efficiency >87%

### Additional control capability:\*

- Enable/Disable function
- Simple 1 or 2 button intensity control
- CDS ambient light sensor control
- Synchronization to display frame-rate capable
- Two-wire(variable resistance) intensity control
- Serial communication control

\* Please contact factory for information

