

### PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

### **General Description**

The AP3706 is a high performance AC/DC power supply controller for battery charger and adapter applications. The device uses Pulse Frequency Modulation (PFM) method to build discontinuous conduction mode (DCM) flyback power supplies.

The AP3706 provides constant voltage, constant current (CV/CC) regulation without requiring an optocoupler and secondary control circuitry. It also eliminates the need of loop compensation circuitry while maintaining stability.

The AP3706 achieves excellent regulation and high power efficiency, the no-load power consumption is less than 200mW at 265VAC input.

The AP3706 is available in SOIC-8 and DIP-8 packages.

### Features

- Primary Side Control for Rectangular Constant Current and Constant Voltage Output
- Eliminates Opto-Coupler and Secondary CV/CC Control Circuitry
- Eliminates Control Loop Compensation Circuitry
- Flyback Topology in DCM Operation
- Random Frequency Modulation to Reduce System EMI
- Valley Turn on of External Power NPN Transistor
- Built-in Soft Start
- Open Circuit Protection
- Over Voltage Protection
- Short Circuit Protection

### Applications

- Adapters/Chargers for Cell/Cordless Phones, PDAs, MP3 and Other Portable Apparatus
- Standby and Auxiliary Power Supplies





Figure 1. Package Types of AP3706



## PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

### **Pin Configuration**





## **Pin Description**

Pin Number	Pin Name	Function
1	CS	The primary current sense
2	VCC	Supply voltage
3	OUT	This pin drives the base of external power NPN switch
4	GND	Ground
5	FB	The voltage feedback from the auxiliary winding
6	VDD	The 5V output of the internal voltage regulator
7	BIAS	This pin sets the bias current inside AP3706 with an external resistor to GND
8	COMP	This pin connects a bypass capacitor for CC function



# PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

## **Functional Block Diagram**





Figure 3. Functional Block Diagram of AP3706



### PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

### **Ordering Information**



Package	Temperature Range	Part Number		Mark	Packing Type	
I ackage		Lead Free	Green	Lead Free	Green	I acking Type
SOIC-8	-40 to 85°C	AP3706M-E1	AP3706M-G1	3706M-E1	3706M-G1	Tube
		AP3706MTR-E1	AP3706MTR-G1	3706M-E1	3706M-G1	Tape & Reel
DIP-8		AP3706P-E1	AP3706P-G1	AP3706P-E1	AP3706P-G1	Tube

BCD Semiconductor's Pb-free products, as designated with "E1" suffix in the part number, are RoHS compliant. Products with "G1" suffix are available in green packages.

### Absolute Maximum Ratings (Note 1)

Parameter	Va	Value		
Supply Voltage VCC	-0.3	-0.3 to 30		
Voltage at CS, BIAS, OUT, VDD, COMP to GND	-0.3	-0.3 to 7		
FB input (Pin 5)	-40	-40 to 10		
Output Current at OUT	Internally	Internally limited		
Power Dissipation at T <sub>A</sub> =25°C	0.6	0.657		
Operating Junction Temperature	1:	150		
Storage Temperature	-65 t	-65 to 150		
Lead Temperature (Soldering, 10s)	31	300		
	SOIC-8	190	0	
Thermal Resistance Junction-to-Ambient	DIP-8	100	°C/W	
ESD (Machine Model)	20	200		

Note 1: Stresses greater than those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "Recommended Operating Conditions" is not implied. Exposure to "Absolute Maximum Ratings" for extended periods may affect device reliability.



# PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

### **Electrical Characteristics**


# ( $V_{CC}$ =15V, $T_A$ =25°C, unless otherwise specified.)

Parameter	Symbol	Conditions	Min	Тур	Max	Unit
UVLO SECTION			•			
Start-up Threshold	V <sub>TH (ST)</sub>		17	18.5	20	V
Minimal Operating Voltage	V <sub>OPR</sub> (min)	After turn on	6.5	7.3	8.1	V
REFERENCE VOLTAGE SECTION	ON					
BIAS Pin Voltage	V <sub>BIAS</sub>	R <sub>BIAS</sub> =200kΩ, Before turn on	1.170	1.205	1.240	V
VDD Pin Voltage	VDD		4.75	5.0	5.25	V
STANDBY CURRENT SECTION	1			•	•	
Start-up Current	I <sub>ST</sub>	$V_{CC} = V_{TH (ST)}$ -0.5V, R <sub>BIAS</sub> =200kΩ, Before turn on		70	80	μΑ
Operating Current	I <sub>CC(OPR)</sub>	R <sub>BIAS</sub> =200kΩ		680	900	μΑ
DRIVE OUTPUT SECTION						
OUT Maximum Current	I <sub>OUT</sub>	R <sub>BIAS</sub> =200kΩ	50			mA
Source	-001		25	30		
CURRENT SENSE SECTION						
Current Sense Threshold	V <sub>CS</sub>		485	505	525	mV
Pre-Current Sense	V <sub>CS(PRE)</sub>		385	410	435	mV
Leading Edge Blanking				430		ns
FEEDBACK INPUT SECTION			•	•		
Feedback Pin Input Leakage Current	I <sub>FB</sub>	V <sub>FB</sub> =4V	10.0	12.5	15.0	μΑ
Feedback Threshold	V <sub>FB</sub>		3.90	4.00	4.10	V
Enable Turn-on Voltage	V <sub>FB(EN)</sub>		-0.9	-0.7	-0.5	V
COMP THRESHOLD VOLTAGE	SECTION	1	1	I	I	
Turn-on Threshold Voltage	V <sub>COMP</sub>		3.42	3.60	3.78	V
PROTECTION SECTION		1	1	1	1	
Over Voltage Protection	V <sub>FB(OVP)</sub>		7	8	9	V



## PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

# **Typical Performance Characteristics**






Figure 4. Start-up Voltage vs. Ambient Temperature

Figure 5. Start-up Current vs. Ambient Temperature




Figure 6. Operating Current vs. Ambient Temperature





Figure 7.  $V_{DD}$  vs. Ambient Temperature



# PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

## **Typical Performance Characteristics (Continued)**








Figure 9. OUT Source Current vs. Bias Resistor



### PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

#### **Operation Description**




Figure 10. Simplified Flyback Converter Controlled by AP3706

Figure 10 illustrates a simplified flyback converter controlled by AP3706.

### **Constant Primary Peak Current**

The primary current ip(t) is sensed by a current sense resistor  $R_{CS}$  as shown in Figure 10.

The current rises up linearly at a rate of:




Figure 11. Primary Current Waveform

As illustrated in Figure 11, when the current ip(t) rises up to Ipk, the switch Q1 turns off. The constant peak current is given by:

Mar. 2009 Rev. 1. 4

The energy stored in the magnetizing inductance LM each cycle is therefore:

So the power transferring from the input to the output is given by:

Where the fsw is the switching frequency. When the peak current Ipk is constant, the output power depends on the switching frequency fsw.

#### **Constant Voltage Operation**

The AP3706 captures the auxiliary winding feedback voltage at FB pin and operates in constant-voltage (CV) mode to regulate the output voltage. Assuming the secondary winding is master, the auxiliary winding is slave during the D1 on-time. The auxiliary voltage is given by:



#### PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

#### **Operation Description (Continued)**

Where the Vd is the diode forward drop voltage.




Figure 12. Auxiliary Voltage Waveform

The output voltage is different from the secondary voltage in a diode forward drop voltage. The diode drop voltage depends on the current. If the secondary voltage is always detected at a constant secondary current, the difference between the output voltage and the secondary voltage will be a fixed Vd. The voltage detection point is at two-thirds of the D1 on-time. The CV loop control function of AP3706 then generates a D1 off-time to regulate the output voltage.

#### **Constant Current Operation**

The AP3706 is designed to work in constant-current (CC) mode. Figure 13 shows the secondary current waveforms.




Figure 13. Secondary Current Waveform

In CC operation, the CC loop control function of AP3706 will keep a fixed proportion between D1 ontime Tons and D1 off-time Toffs by discharging or charging the capacitance connected in COMP pin. The fixed proportion is

Tons	_ 4	
Toffs -	$\overline{3}$	(6)

Mar. 2009 Rev. 1. 4

The relationship between the output constant-current and secondary peak current Ipks is given by:

At the instant of D1 turn-on, the primary current transfers to the secondary at an amplitude of:

Thus the output constant-current is given by:

$$Iout = \frac{1}{2} \times \frac{N_P}{N_S} \times Ipk \times \frac{Tons}{Tons + Toffs} = \frac{2}{7} \times \frac{N_P}{N_S} \times Ipk$$
.....(9)

#### Leading Edge Blanking

When the power switch is turned on, a turn-on spike will occur on the sense-resistor. To avoid falsetermination of the switching pulse, a 430ns leadingedge blanking is built in. During this blanking period, the current sense comparator is disabled and the gate driver can not be switched off.

#### **CCM Protection**

The AP3706 is designed to operate in discontinuous conduction mode (DCM) in both CV and CC modes. To avoid operating in continuous conduction mode (CCM), the AP3706 detects the falling edge of the FB input voltage on each cycle. If a 0.1V falling edge of FB is not detected, the AP3706 will stop switching.


#### **OVP & OCkP**


The AP3706 includes output over-voltage protection (OVP) and open circuit protection (OCkP) circuitry as shown in Figure 14. If the voltage at FB pin exceeds 8V, 100% above the normal detection voltage, or the -0.7V falling edge of the FB input can not be monitored, the AP3706 will immediately shut off and enters hiccup mode. The AP3706 sends out a fault detection pulse every 8ms in hiccup mode until the fault has been removed.



# PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

**Operation Description (Continued)** 





# **Typical Application**




Figure 15. 5V/1A Output for Battery Charger of Mobile Phone

Mar. 2009 Rev. 1. 4




## PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

### **Mechanical Dimensions**

Unit: mm(inch)





Note: Eject hole, oriented hole and mold mark is optional.

Mar. 2009 Rev. 1. 4




## PRIMARY SIDE CONTROL IC FOR OFF-LINE BATTERY CHARGERS AP3706

### Mechanical Dimensions (Continued)

DIP-8

Unit: mm(inch)



Note: Eject hole, oriented hole and mold mark is optional.

Mar. 2009 Rev. 1. 4



### **BCD Semiconductor Manufacturing Limited**

http://www.bcdsemi.com

#### IMPORTANT NOTICE

BCD Semiconductor Manufacturing Limited reserves the right to make changes without further notice to any products or specifications herein. BCD Semiconductor Manufacturing Limited does not assume any responsibility for use of any its products for any particular purpose, nor does BCD Semiconductor Manufacturing Limited assume any liability arising out of the application or use of any its products or circuits. BCD Semiconductor Manufacturing Limited does not convey any license under its patent rights or other rights nor the rights of others.

#### MAIN SITE

#### - Headquarters

**BCD Semiconductor Manufacturing Limited** No. 1600, Zi Xing Road, Shanghai ZiZhu Science-based Industrial Park, 200241, China Tel: +86-21-24162266, Fax: +86-21-24162277

#### REGIONAL SALES OFFICE Shenzhen Office

Shanghai SIM-BCD Semiconductor Manufacturing Co., Ltd., Shenzhen Office Unit A Room 1203, Skyworth Bldg., Gaoxin Ave.1.S., Nanshan District, Shenzhen, China Tel: +86-755-8826 7951

Tel: +86-755-8826 7951 Fax: +86-755-8826 7865

#### - Wafer Fab

Shanghai SIM-BCD Semiconductor Manufacturing Co., Ltd. 800 Yi Shan Road, Shanghai 200233, China Tel: +86-21-6485 1491, Fax: +86-21-5450 0008

Taiwan Office

BCD Semiconductor (Taiwan) Company Limited 4F, 298-1, Rui Guang Road, Nei-Hu District, Taipei, Taiwan Tel: +886-2-2656 2808

Tel: +886-2-2656 2808 Fax: +886-2-2656 2806 USA Office BCD Semiconductor Corp. 30920 Huntwood Ave. Hayward, CA 94544, USA Tel : +1-510-324-2988 Fax: +1-510-324-2788