# HR395.5 395.5MHz One-Port SAW Resonator



Approved by:

Checked by:

Issued by:

# **SPECIFICATION**

PRODUCT: SAW RESONATOR

MODEL: HR395.5 F-11


# HOPE MICROELECTRONICS CO., LIMITED

Tel:+86-755-82973806 Fax:+86-755-82973550 E-mail: <u>sales@hoperf.com</u> http://www.hoperf.com Page 1 of 1

HR395.5

The HR395.5 is a true one-port, surface-acoustic-wave (**SAW**) resonator in a low-profile metal **F-11** case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at **395.500** MHz.

#### 1.Package Dimension (F-11)




2.Marking

# HR395.5

Color: Black or Blue


## **4.Typical Application Circuits**

1) Low-Power Transmitter Application




# 5.Typical Frequency Response

▶1:Transmission /H Log Mag 5.0 dB/ Ref -1.50 dB ▷2:Off




Pin	Configuration				
1,4	Input / Output				
2/3	Case Ground				
Dimension	Data (unit: mm)				
A	11.0±0.3				
В	4.5±0.3				
С	3.2±0.3				
D	0.45±0.1				
E	5.0±0.5				
F	2.54±0.2				


3.Equivalent LC Model and Test Circuit



2) Local Oscillator Application



## **6.Temperature Characteristics**



The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

 D
 0.

 E
 5

 F
 2.

#### 7.Performance

#### 7-1.Maximum Ratings

Rating	Value	Unit	
CW RF Power Dissipation	Ρ	0	dBm
DC Voltage Between Any two Pins	V <sub>DC</sub>	± 30	V
Storage Temperature Range	T <sub>stg</sub>	-40 to +85	
Operating Temperature Range	T <sub>A</sub>	-10 to +60	

#### 7-2. Electronic Characteristics

	Characteristic	Sym	Minimum	Typical	Maximum	Unit
Center Frequency (+25)	Absolute Frequency	f <sub>C</sub>	395.425		395.575	MHz
	Tolerance from 395.500 MHz	$\Delta f_{C}$		±75		kHz
Insertion Loss		IL		1.3	1.8	dB
Quality Factor	Unloaded Q	QU		11,240		
	50 $\Omega$ Loaded Q	QL		1,550		
Temperature Stability	Turnover Temperature	T <sub>0</sub>	25		55	
	Turnover Frequency	f <sub>0</sub>		f <sub>C</sub>		kHz
	Frequency Temperature Coefficient	FTC		0.032		ppm/ <sup>2</sup>
Frequency Aging Absolute Value during the First Year		f <sub>A</sub>		10		ppm/yr
DC Insulation Resistance Between Any Two Pins			1.0			MΩ
RF Equivalent RLC Model	Motional Resistance	R <sub>M</sub>		16	23	Ω
	Motional Inductance	L <sub>M</sub>		72.3908		μH
	Motional Capacitance	См		2.2393		fF
	Pin 1 to Pin 4 Static Capacitance	C <sub>0</sub>	2.0	2.3	2.6	pF

## **(i)** CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

#### C 2003. All Rights Reserved.

- 1. The center frequency, f<sub>C</sub>, is measured at the minimum IL point with the resonator in the 50 test system.
- 2. Unless noted otherwise, case temperature  $T_C = +25^{\circ}C \pm 2^{\circ}C$ .
- Frequency aging is the change in f<sub>c</sub> with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature,  $T_0$ , is the temperature of maximum (or turnover) frequency,  $f_0$ . The nominal frequency at any case temperature,  $T_C$ , may be calculated from:  $f = f_0 [1 FTC (T_0 T_C)^2]$ .
- 5. This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance C<sub>0</sub> is the measured static (nonmotional) capacitance between Pin1 and Pin4. The measurement includes case parasitic capacitance.
- 6. Derived mathematically from one or more of the following directly measured parameters:  $f_c$ , IL, 3 dB bandwidth,  $f_c$  versus  $T_c$ , and  $C_0$ .
- 7. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.
- 10. For questions on technology, prices and delivery, please contact our sales offices or e-mail sales@hoperf.com.