

Surface Mount VCTCXO




ECVT-560 Series

- Very Low Profile
- Low Current Consumption
- Excellent Stability
- 3 Volt Supply
- Custom Options



Parameter	ECVT560	Option
Frequency Range	9.60MHz to 26.0MHz	Specify
Frequency	<u>+</u> 2.5ppm -30°C to +75°C	A
Stability	<u>+</u> 2.5ppm -10°C to +60°C	J
•	+2.0ppm -30°C to +75°C	Н
	<u>+</u> 1.5ppm -20 ^o C to +70 ^o C	G
	<u>+</u> 1.0ppm -10 ^o C to +60 ^o C	F
	220	
Storage Temp	-30° to +85°C	
Frequency vs	<u>+</u> 0.3ppm max	
Supply		
Frequency vs	<u>+</u> 0.3ppm max	
Load		
Aging	<u>+</u> 1.0ppm max	
Supply Voltage	+3.0V and +5.0V	Specify
Supply Current	2.0mA	
Output	0.8V p-p	
Output Load	10KΩ // 10pF	
Frequency Control		
(Internal trimmer)	+/-6ppm min +/-15ppm max	1
(External trimmer)	-	Е
Voltage Control	1.5V +/-1V (Vcc 3V)	
	2.5V +/-2V (Vcc 5V)	
Start-up Time	5mS max	

Environmental & Mechanical						
Humidity	+40 ⁰ C +/-2 ⁰ C					
	90 to 95% for 8 Hours					
Thermal	One Hundred cycles					
Shock	-40 ⁰ C to +85 ⁰ C 30mins Ea					
Vibration	5 to 36 Hz 1.5mm amplitude					
	26 to 500Hz 4g acceleration					
Soldering						
Condition	230 ⁰ C +/-10 ⁰ for 45s max					



Α	В	С	D	E	F	G	Н		
11.4	9.6	2.5	7.62	1.3	1.0	7.00	2.54		
Dimensions in mm									
Pin		1	2	3	4	5 to 8	5 to 8		
Conne	ction	Vc	Gnd	O/P	+Vcc	Keep	Keep Floating		

ECM Electronics Limited, Penmaen House, Ashington, West Sussex, RH20 3JR, UK Tel: +44(0)1903 892810: Fax: +44(0)1903 892738. Email: ecm@ecmelectronics.co.uk