

# Audio/video buffer and four-channel SD/PS/HD video filter


Data brief

#### **Features**

- I<sup>2</sup>C bus control
- Video section:
  - Selectable 7-MHz/15-MHz/30-MHz, lowpass filters, plus bypass, on three encoder video inputs
  - 7-MHz, low-pass filter on one encoder video input
  - DC-coupled inputs
  - Each output is capable of driving an AC- or DC-coupled, 150- $\Omega$  video load at 3 V pp and CVBS output can drive a dual, 75- $\Omega$  video load
  - Fixed gain of 6 dB for each channel
  - Selective video output muting of HD and SD channels

#### Audio section:

- Stereo sound capability
- Differential or single-ended audio inputs
- Audio outputs drive 2-kΩ loads at 3 V RMS
- Selectable audio gain of 0 to 28 dB
- Audio output muting
- 9 V to 12 V single supply operation
- Pop-noise suppression management
- Low power mode
  - Audio/video standby function



### **Applications**

- Set-top boxes (IP, cable, satellite, terrestrial)
- Integrated digital TV plug-in
- Blu-ray and DVD players

## Description

The STV6437 is a fully integrated solution for filtering and buffering standard-definition, progressive-scan and high-definition signals, and buffering stereo audio signals from the MPEG decoder of a digital receiver, Blu-ray or DVD player, or iDTV plug-in.

The STV6437 embeds four buffers with low-pass filters, three for HD (selectable 7/15/30 MHz) and one for SD (7 MHz), and a dual audio amplifier that operates with either differential or single-ended inputs.

Table 1. Device summary

Order code	Temperature range	Package	Packaging
STV6437AJ	0 to 70 °C	VFQFPN-28 (5 $\times$ 5 mm <sup>2</sup> ) EPD	Tray
STV6437AJT	0 to 70 °C	VFQFPN-28 (5 $\times$ 5 mm <sup>2</sup> ) EPD	Tape and reel

Introduction STV6437

### 1 Introduction

The STV6437 is an I<sup>2</sup>C-controlled integrated circuit for filtering and buffering audio and video signals in any consumer electronics application with HD component and SD analog outputs. It can be used in products such as HD set-top boxes or DVD/BD players and recorders.

The STV6437 has a high level of integration and requires only the usual passive components for decoupling and termination. The tiny package VFQFPN-28 ensures a small footprint.

The STV6437 is one of the family of three, pin-compatible products (Figure 1) that complete the new generation of audio and video switches and buffers from STMicroelectronics. Together they cover, both technically and price-wise, the whole market spectrum from mid-range SD retail (zapper set-top boxes or basic recorders) up to DVR HD operators (set-top boxes or recorders with HD component output).

Features	Benefits
DC-coupled video inputs.	Reduces component count.
AC- and DC-coupled high-drive capability video outputs (for 70- $\Omega$ (minimum) loads).	Connects to any type of display and drives several composite and RF modulator outputs without external active components.
Smart pop-noise manager.	Allows silent swap between active and standby modes.
Selective standby command for audio and each set of SD or HD video outputs.	As low as 4-mW standby consumption supporting compliance to 0.5-W standby requirements.
8-step selectable audio gain up to +28 dB, supporting output of 3.1 V RMS (minimum).	Easy fine-tune of THD and SNR depending on requirements, whilst matching any specific audio output level, including China Cable, and saving external op-amps.
Pin-compatibility with two other products.	Combines single-device space-saving (up to 50%) benefits with commodity price/flexibility benefits to allow a single PCB design covering the entire market spectrum.
Pin-compatibility with STV6440AJ.	Provides dual-source solution at no cost premium in case of market shortage or sudden rise in demand.

STV6437 Revision history

Analog audio/video Pr Pb Y S-Video
OOO
R L CVBS Set-top box market segments **©**⊚ R L CVBS High-end STV6418AH STV6437BH HD Mid-range STV6417AG STV6437AJ Low-end STV6430AG High-end STV6432AJ SD Mid-range Low-end Pin-compatible ICs LQFP-48 / TQFP-48 exposed pad

Figure 1. Pin-compatible devices

# 2 Revision history

Table 2. Document revision history

Date	Revision	Changes
12-Aug-2011	1	Initial release.

#### Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY TWO AUTHORIZED ST REPRESENTATIVES, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2011 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

4