

SMA Male Connector Solder Attachment 0.062 inch End Launch PCB, .020 inch x .010 inch Contact



TECHNICAL DATA SHEET

	PE	E49	13

SMA Male Connector Solder Attachment 0.062 inch End Launch PCB, .020 inch x .010 inch Contact				
Configuration Connector Connector Interface Type Cable Attachment Method (Shield/Contact) Body Style	SMA Male 0.062 inch End Launch Solder Straight			
Electrical Specifications Impedance, Ohms	50			
Mechanical Specifications				
Size Length, in [mm] Width/Dia., in [mm] Height, in [mm] Weight, Ibs [g]	0.68 [17.27] 0.375 [10] 0.312 [7.92] 0.013 [5.9]			
Connector Type Contact Material and Plating Coupling Nut Material and Plating Hex Size, in. Torque, in-lbs [Nm] Body Material and Plating Dielectric Type	SMA Male Gold Brass, Gold 5/16 5 [0.57] Brass, Gold PTFE			
Compliance Certifications (visit www.Pasternack.co RoHS Compliant	m for current document) Yes			
Plotted and Other Data Notes:	Values at 25 °C, sea level			
	Launch PCB, .020 inch x .010 inch Contact from Pasternack Enter- onal orders. Our RF, microwave and fiber optic products maintain a the industry.			

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMA Male Connector Solder Attachment 0.062 inch End Launch PCB, .020 inch x .010 inch Contact PE4913

URL: http://www.pasternack.com/sma-male-standard-0.062-end-launch-connector-pe4913-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com



PE4913 CAD Drawing

SMA Male Connector Solder Attachment 0.062 inch End Launch PCB, .020 inch x .010 inch Contact

