


Tel: +44 118 979 1238 Fax: +44 118 979 1283

Email: info@actcrystals.com

The ACTR9002/916.5/QCC4A is a true one-port, surface-acoustic-wave (SAW) resonator in a surface-mount ceramic QCC4A case. It provides reliable, fundamental-mode, quartz frequency stabilization i.e. in transmitters or local oscillators operating at 916.500 MHz.

1.Package Dimension (QCC4A)




2.

Pin	Configuration		
1	Input / Output		
3	Output / Input		
2/4	Case Ground		


Sign	Data (unit: mm)	Sign	Data (unit: mm)
Α	1.2	D	1.4
В	0.8	Е	5.0
С	0.5	F	3.5

3. Equivalent LC Model and Test Circuit




4. Typical Application Circuits

1) Low-Power Transmitter Application



2) Local Oscillator Application



Issue: 1.1 C1

Date: March 2010

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered

For quotations or further information please contact us at: 3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK

http://www.actcrystals.com




Tel: +44 118 979 1238 Fax: +44 118 979 1283 Email: info@actcrystals.com

Issue: 1.1 C1


Date: March 2010

6.Temperature Characteristics



The curve shown above accounts for resonator contribution only and does not include oscillator temperature characteristics.

5. Typical Frequency Response



7.Performance

7-1.Maximum Ratings

Rating	Value	Units
CW RF Power Dissipation	0	dBm
DC Voltage Between Terminals	±30V	VDC
Case Temperature	-40 to +85	°C
Soldering Temperature	+250	°C

7-2. Electronic Characteristics

	Characteristic	Sym	Minimum	Typical	Maximum	Units
Centre Frequency (+25 °C)	Absolute Frequency	f _C	916.350		916.650	MHz
	Tolerance from 916.500 MHz	Δf_{C}		±150		kHz
Insertion Loss		ΙL		1.5	2.2	dB
Quality Factor	Unloaded Q	Q _U		10,020		
	50 Ω Loaded Q	Q_L		1,500		
	Turnover Temperature	T ₀	25		55	°C
Temperature Stability	Turnover Frequency	f ₀		f _C		kHz
	Frequency Temperature Coefficient	FTC		0.032		ppm/°C ²
Frequency Aging Absolute Value during the First Year		fA		≤10		ppm/yr
DC Insulation Resistance Between Any Two Terminals			1.0			ΜΩ
RF Equivalent RLC Model	Motional Resistance	R_{M}		19	29	Ω
	Motional Inductance	L _M		31.0132		μН
	Motional Capacitance	См		0.9734		fF
	Shunt Static Capacitance	C ₀	1.8	2.1	2.4	pF

i CAUTION: Electrostatic Sensitive Device. Observe precautions for handling!

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

ISO9001: 2000 Registered

For quotations or further information please contact us at: 3 The Business Centre, Molly Millars Lane, Wokingham, Berks, RG41 2EY, UK

http://www.actcrystals.com



Tel: +44 118 979 1238 Fax: +44 118 979 1283

Email: info@actcrystals.com

- The centre frequency, f_C, is measured at the minimum IL point with the resonator in the 50 Ω test system.
 Unless noted otherwise, case temperature T_C = +25°C±2°C.
 Frequency aging is the change in f_C with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.
- 4. Turnover temperature, To, is the temperature of maximum (or turnover) frequency, fo. The nominal frequency at any case temperature, T_C , may be calculated from: $f = f_0 [1 - FTC (T_0 - T_C)^2]$.
- This equivalent RLC model approximates resonator performance near the resonant frequency and is provided for reference only. The capacitance Co is the measured static (non-motional) capacitance between the two terminals. The measurement includes case parasitic capacitance.
- 6. Derived mathematically from one or more of the following directly measured parameters: f c, IL, 3 dB bandwidth, f_C versus T_C, and C₀.
- 7. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- 8. Typically, equipment utilizing this device requires emissions testing and government approval, which is the responsibility of the equipment manufacturer.
- 9. Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.

In keeping with our ongoing policy of product evolvement and improvement, the above specification is subject to change without notice.

Issue: 1.1 C1