

.

SDT400

DC Input Optocoupler

DESCRIPTION

The SDT400 consists of a phototransistor optically coupled to a light emitting diode. Optical coupling between the input LED and output phototransistor allows for high isolation levels while maintaining low-level DC signal control capability. The SDT400 provides an optically isolated method of controlling many interface applications such as telecommunications, industrial control and instrumentation circuitry.

FEATURES

- High input-to-output isolation package (5000 Vrms)
- Low input power consumption
- High stability
- Miniature 4 pin DIP package
- CTR Range 50-600%

APPLICATIONS


- Registers, copiers, Automatic Vending Machines
- System appliances, measuring instruments
- Computer terminals, PLCs
- Telecommunications, telephones
- Home Appliances
- Digital logic inputs
- Microprocessor inputs
- Switching power supply

OPTIONS/SUFFIXES*

- -H .04" (10.16mm) lead spacing (VDE0884)
- -S Surface Mount Option
- -TR Tape and Reel Option

NOTE: Suffixes listed above are not included in marking on device for part number identification.

SCHEMATIC DIAGRAM



ABSOLUTE MAXIMUM RATINGS*

PARAMETER	UNIT	MIN	TYP	MAX
Storage Temperature	°C	-55		125
Operating Temperature	°C	-40		100
Input Forward Current	mA			50
Input Peak Forward Current	A			1
Reverse Input Control Voltage	V			6
Total Power Dissipation	mW			200

*The values indicated are absolute stress ratings. Functional operation of the device is not implied at these or any conditions in excess of those defined in electrical characteristics section of this document. Exposure to Absolute Ratings may cause permanent damage to the device and may adversely affect reliability.

APPROVALS

- UL and C-UL Approved, File #E201932
- VDE Approved, Lic # 40011227



DC Input Optocoupler


ELECTRICAL CHARACTERISTICS - 25°C

PARAMETER UNIT MIN TYP MAX TEST CONDITIONS						
FARAMETER		IVIIIN	ITP	IVIAA	TEST CONDITIONS	
INPUT SPECIFICATIONS						
Forward Voltage	V		1.2	1.4	lf = 20mA	
Reverse Current	μA			10	Vr = 4V	
OUTPUT SPECIFICATIONS						
Collector-Emitter Breakdown Voltage	V	60			lc = 10uA	
Emitter-Collector Breakdown Voltage	V	6			le = 10uA	
Dark Current	μA			0.1	Vce = 20V	
Floating Capacitance	рF		0.6	1	V = 0, f=1MHz	
Saturation Voltage	V		0.1	0.2	lf = 20mA, lc = 1mA	
Current Transfer Ratio	%	50		600	lf = 5mA, Vce = 5V	
Rise Time	μS		4		Ic = 2mA, Vcc = 2V, Rc = 100 ohms	
Fall Time	μS		3		Ic = 2mA, Vcc = 2V, Rc = 100 ohms	
COUPLED SPECIFICATIONS						
Isolation Voltage	V	5000			T = 1 minute	
Isolation Resistance	GΩ	50				
CTR CLASSIFICATION						
-A	%	60		160		
-В	%	130		260		
-C	%	200		400		
-D	%	300		600		
-E	%	50		600		



DC Input Optocoupler


PERFORMANCE DATA





DC Input Optocoupler

PERFORMANCE DATA






DC Input Optocoupler


MECHANICAL DIMENSIONS

4 PIN DUAL IN-LINE PACKAGE (SDT400)




0.25


13.00



TOLERANCE : ±0.2mm

4 PIN SURFACE MOUNT DEVICE (SDT400-S)







TOLERANCE : ±0.2mm

4 PIN H TYPE WITH 0.4" LEAD SPACING (SDT400-H)



13.00





TOLERANCE : ±0.2mm



DC Input Optocoupler

DISCLAIMER

Solid State Optronics (SSO) makes no warranties or representations with regards to the completeness and accuracy of this document. SSO reserves the right to make changes to product description, specifications at any time without further notice. SSO shall not assume any liability arising out of the application or use of any product or circuit described herein. Neither circuit patent licenses nor indemnity are expressed or implied.

Except as specified in SSO's Standard Terms & Conditions, SSO disclaims liability for consequential or other damage, and we make no other warranty, expressed or implied, including merchantability and fitness for particular use.

LIFE SUPPORT POLICY

SSO does not authorize use of its devices in life support applications wherein failure or malfunction of a device may lead to personal injury or death. Users of SSO devices in life support applications assume all risks of such use and agree to indemnify SSO against any and all damages resulting from such use. Life support devices are defined as devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when used properly in accordance with instructions for use can be reasonably expected to result in significant injury to the user, or (d) a critical component in any component of a life support device or system whose failure can be reasonably expected to cause failure of the life support device or system, or to affect its safety or effectiveness.