

QUICKSWITCH[®] PRODUCTS HIGH-SPEED CMOS QUICKSWITCH QUAD 2:1 MUX/DEMUX

FEATURES:

- · Enhanced N channel FET with no inherent diode to Vcc
- 5 Ω bidirectional switches connect inputs to outputs
- Pin compatible with the 74F257, 74FCT257, and 74FCT257T
- · Zero propagation delay, zero ground bounce
- · Undershoot clamp diodes on all switch and control inputs
- TTL-compatible control inputs
- Available in SOIC, QSOP, and S1 packages

DESCRIPTION:

The QS3257 is a high-speed CMOS LVTTL-compatible Quad 2:1 multiplexer/demultiplexer. The QS3257 is a function and pinout compatible QuickSwitch version of the 74F257, 74FCT257, and the 74ALS/AS/LS257 Quad 2:1 multiplexers. The low ON resistance of the QS3257 allows inputs to be connected to outputs without adding propagation delay and without generating additional ground bounce noise.


Mux/Demux devices provide an order of magnitude faster speed than equivalent logic devices.

The QS3257 is characterized for operation at -40°C to +85°C.

APPLICATIONS:

- Logic replacement
- · Video, audio, graphics switching, muxing
- · Hot-swapping, hot-docking
- Voltage translation (5V to 3.3V)
- Bus funneling

FUNCTIONAL BLOCK DIAGRAM



1

The IDT logo is a registered trademark of Integrated Device Technology, Inc.


INDUSTRIAL TEMPERATURE RANGE

FEBRUARY 2001

HIGH-SPEED CMOS QUICKSWITCH QUAD 2:1 MUX/DEMUX

INDUSTRIAL TEMPERATURE RANGE

PINCONFIGURATION



SOIC/ QSOP/ S1 TOP VIEW

ABSOLUTE MAXIMUM RATINGS⁽¹⁾

Symbol	Description	Max	Unit
VTERM ⁽²⁾	Supply Voltage to Ground	-0.5 to +7	V
VTERM ⁽³⁾	DC Switch Voltage Vs	–0.5 to +7	V
VTERM ⁽³⁾	DC Input Voltage VIN	–0.5 to +7	V
VAC	AC Input Voltage (pulse width \leq 20ns)	-3	V
Ιουτ	DC Output Current	120	mA
Рмах	Maximum Power Dissipation (TA = 85°C)	0.5	W
Tstg	Storage Temperature	-65 to +150	°C

NOTE:

 Stresses greater than those listed under ABSOLUTE MAXIMUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

2. Vcc terminals.

3. All terminals except Vcc.

CAPACITANCE

 $(TA = +25^{\circ}C, f = 1.0MHz, VIN = 0V, VOUT = 0V)$

Pins		Тур.	Max. ⁽¹⁾	Unit
Control Pins	4	5	pF	
Quickswitch Channels	Demux	5	7	pF
(Switch OFF)	Mux	8	9	

NOTE:

1. This parameter is measured at characterization but not tested.

PINDESCRIPTION

Pin Names	I/O	Description		
lxx		DataInputs		
S I		SelectInput		
ĒI		EnableInput		
Ya - Yd O		Data Outputs		

FUNCTION TABLE⁽¹⁾

Enable		Outputs				
Ē	S	Ya	Υв	Yc	Yd	Function
Н	Х	Hi-Z	Hi-Z	Hi-Z	Hi-Z	Disconnected
L	L	loa	Іов	loc	lod	Select0
L	Н	I1A	I1B	l1C	l1d	Select 1

NOTE:

1. H = HIGH Voltage Level

L = LOW Voltage Level

X = Don't Care

Z = High-Impedance

DC ELECTRICAL CHARACTERISTICS OVER OPERATING RANGE

 ${\sf Following\,Conditions\,Apply\,Unless\,Otherwise\,Specified:}$

Industrial: TA = -40° C to $+85^{\circ}$ C, VCC = 5.0V $\pm 5\%$


Symbol	Parameter	Test Conditions	Min.	Typ. ⁽¹⁾	Max.	Unit
Vih	Input HIGH Level	Guaranteed Logic HIGH for Control Pins	2	_	—	V
Vil	Input LOW Level	Guaranteed Logic LOW for Control Pins	_	_	0.8	V
lin	Input LeakageCurrent (Control Inputs) ⁽²⁾	$0V \le VIN \le VCC$	_	—	±1	μA
loz	Off-State Output Current (Hi-Z)	$0V \le VOUT \le VCC$	_	_	±1	μA
Ron	Switch ON Resistance	VCC = Min., $VIN = 0V$, $ION = 30mA$	_	5	7	Ω
		VCC = Min., $VIN = 2.4V$, $ION = 15mA$	—	10	15	
Vp	Pass Voltage ⁽²⁾	$V_{\text{IN}} = V_{\text{CC}} = 5V, \text{ lout} = -5\mu A$	3.7	4	4.2	V

NOTES:

1. Typical values are at Vcc = 5.0V, TA = 25°C.

2. Pass Voltage is guaranteed but not production tested.

TYPICAL ON RESISTANCE vs VIN AT Vcc = 5V



VIN (Volts)

POWER SUPPLY CHARACTERISTICS

Symbol	Parameter	Test Conditions ⁽¹⁾	Max.	Unit
lcco	Quiescent Power Supply Current	Vcc = Max., VIN = GND or Vcc, f = 0	3	μΑ
Δlcc	Power Supply Current per Control Input HIGH ⁽²⁾	Vcc = Max., VIN = 3.4V, f = 0	1.5	mA
ICCD	Dynamic Power Supply Current per MHz ⁽³⁾	Vcc = Max., I and Y pins open Control Inputs Toggling at 50% Duty Cycle	0.25	mA/MHz

NOTES:

1. For conditions shown as Min. or Max., use the appropriate values specified under DC Electrical Characteristics.

2. Per TLL driven input (VIN = 3.4V, control inputs only). I and Y pins do not contribute to Δ Icc.

3. This current applies to the control inputs only and represents the current required to switch internal capacitance at the specified frequency. The I and Y inputs generate no significant AC or DC currents as they transition. This parameter is guaranteed but not production tested.

SWITCHING CHARACTERISTICS OVER OPERATING RANGE

 $T_A = -40^{\circ}C \text{ to } +85^{\circ}C, V_{CC} = 5.0V \pm 5\%;$

 $C_{LOAD} = 50 pF$, $R_{LOAD} = 500 \Omega$ unless otherwise noted.

Symbol	Parameter	Min. ⁽¹⁾	Тур.	Max.	Unit
t PLH	Data Propagation Delay ^(2,3)	—	—	0.25 ⁽³⁾	ns
t PHL	Ix to Y				
tрzн	Switch Turn-on Delay	0.5	—	5.2	ns
tPZL	Sx to Y				
tрzн	Switch Turn-on Delay	0.5	—	4.8	ns
tPZL	Ex to Y				
tphz	Switch Turn-off Delay ⁽²⁾	0.5	_	5	ns
tplz	Ex to Y, Sx to Y				


NOTES:

1. Minimums are guaranteed but not production tested.

2. This parameter is guaranteed but not production tested.

^{3.} The bus switch contributes no propagation delay other than the RC delay of the ON resistance of the switch and the load capacitance. The time constant for the switch alone is of the order of 0.25ns for C_L = 50pF. Since this time constant is much smaller than the rise and fall times of typical driving signals, it adds very little propagation delay to the system. Propagation delay of the bus switch, when used in a system, is determined by the driving circuit on the driving side of the switch and its interaction with the load on the driven side.

ORDERING INFORMATION





CORPORATE HEADQUARTERS 2975 Stender Way Santa Clara, CA 95054 *for SALES:* 800-345-7015 or 408-727-6116 fax: 408-492-8674 www.idt.com for Tech Support: logichelp@idt.com (408) 654-6459